Relativistic Heavy Ion Collider Magnet Division Procedure	Proc. No.:	RHIC-MAG-R-7306
Wagnet Division Procedure	Issue Date:	May 22, 1989
	Rev. No.:	<u>A</u>
	Rev. Date:	May 29, 1992
Class: Electrical Testing Title: RHIC High Precision Resistance Insulation Test		

	Cognizant Engineer:	Signature on File BNL Magnet Division		
•	Approved by:	Signature on File		
		Head, Electrical Systems Section,		
		<b>BNL Magnet Division</b>		

REVISION RECORD

Rev. No.	Date	Page	Subject	Approval
A	5/29/92		Initial Release	

RHIC-MAG-R-7306A Page 1 of 3

### 1. Scope:

This procedure describes the method of using a high precision Giga-Ohmmeter or Digital Volt Meter for low voltage insulation tests. This test is typically used for insulation tests where the component under test cannot withstand a 1kV Megger or hypot test.

#### 2. Applicable Documents:

Equipment Manufacturers Instruction/Operation Manual(s).

## 3. <u>Requirements</u>:

Data Sheet - RHIC High Precision Resistance Insulation Test.

## 3.1 Equipment:

Suitable 6-1/2 digit Digital Volt Meter. Basic accuracy, 0.005%, DC. Maximum resistance (or O.L. - "Over Load"): 1.0 Gigaohms or greater. (Typical meter model: HP 3457A or equivalent).

#### 3.2 Procedure:

- 3.2.1 Basic Ohmmeter operation. (Also see manufacturers manual):
- 3.2.1.1 Turn unit on. Self check OK. All display segments OK.
- 3.2.1.2 Select lowest two-wire resistance range.
- 3.2.1.3 Short probes together. Verify that meter reads 0 or < 1 Ohm.
- 3.2.1.4 Select highest two-wire resistance range.

Short probes. Verify reading of 0.

Open circuit probes. Verify O.L. or > 1.0 Gigaohm reading.

- 3.2.2 High resistance measurement or insulation test:
- 3.2.2.1 Perform OHMS AUTOCAL operation before using extended (Gigaohm) range.
- 3.2.2.2 Select highest two-wire resistance range (or auto).
- 3.2.2.3 Momentarily short probes together to verify operation.

RHIC-MAG-R-7306A Page 2 of 3

- 3.2.2.4 Connect probes across circuit to be measured and read resistance value or verify O.L. or > 1.0 Gigaohm reading. Record resistance on data sheet.
- 3.2.2.5 Disconnect probes from circuit.
- 4. Quality Assurance Provisions:
- 4.1 The Quality Assurance Provisions of this procedure requires compliance with the procedural instructions contained herein and the recording of test results on the attached data sheet.
- 5. <u>Preparation for Delivery</u>:

N/A

RHIC-MAG-R-7306A Page 3 of 3

#### DATA SHEET

# **RHIC High Precision Resistance Insulation Test**

Magnet No				
Coil No.				
Measured Resistan	ice		$\Omega$ .	
Comments:		Above work done by:		ork done by:
			Name &	Life No., Date
			<u> </u>	
	<u>List of Equi</u>	pment Used for M	<u>easurements</u>	
Nomenclature	Manufacturer	Model	Serial No.	BNL Bar Code
Remarks:				